V-TAC

Meaningful Innovation.

# Portable Power Station

# 300W

- ◎ Upgrade to LiFePO4 battery capacity 288Wh, 10 outlets
- ◎ 1 x DC head 7909 input charging port: adapter charging (24V/2.5A), car charging (12V), solar charging (12-24V 120W MAX)
- ◎ 2 x DC head 5521 output port and 1 x automobile auxiliary power outlet(total 12V/8A)
- ◎ Speed charger QC 3.0 Output x 2，TYPE-C：Output PD18W X1，TYPE-C：Output PD65W
- ◎ 1 x EU / BS standard AC ports
- ◎ LED Flashlight with SOS
- ◎ Quiet noise level during operation
- ◎ Over-current, Over-voltage , over-temperature and Short Circuit Protections 9, Cycle life: 2000 Cycless

V-TAC.EU | VTACEXPORTS.COM

FC CE RoHS PSE

V-TAC

Meaningful Innovation.

# 15W Wireless charger

## LISTING DETAILS

| | |
|---|---|
| Model: | **VT-303N** |
| SKU Code: | **EU-Plug -11625 \| BS-Plug -11740** |
| EAN Code: | **EU-Plug- 3800170200074**<br>**BS-Plug -3800170203266** |

## MASTER BOX PACKAGING

| | |
|---|---|
| Qty: | **1pc/box** |
| Net Weight : | **4.3 kgs** |
| Product Size : | **W*H*L 249*171.5*208mm** |

## GENERAL DATA

| | | | |
|---|---|---|---|
| **BATTERY** | Battery capacity | LiFePO4(IRF32135 19.2V 15Ah/288Wh) | |
| | Cell model | IRF32135 | |
| **DC/INPUT** | DC 7909 INPUT | 12-20V 120W max Charger | Parallel input |
| | XT60 Solar Charger | 12-24V 120W max Charger | |
| **USB/OUTPUT** | USB1 Output | 18W 5V3.5A | |
| | USB2 Output | QC 3.0 18W 5V3A/9V2A/12V1.5A | |
| | TYPE-C 1 Output | PD18W ,5V3A/9V2A/12V1.5A | |
| | TYPE-C2 Output | PD65W ,5V3A / 9V3A / 12V3A / 15V3A / 20V3.25A | |
| **DC OUTPUT** | DC 1 Output | 12V/8A | 100W shared |
| | DC 2 Output | 12V/8A | |
| | Auxiliary Power Outlet | 12V/8A | |
| **AC OUTPUT** | AC Output 1 | AC Power Output 230V Sine WAVE 300W PEAK 500W | |
| | Output Frequency max | Sine WAVE 300W PEAK 500W | |
| | Frequency | 50Hz | |
| **WIRELESS CHARGER** | DC | 15W 5V 3A | |
| **LED LIGHTING** | Power | 3W | |
| | Mode | High-Light/Low-light/SOS/Flash | |